

NFPA 70E® Table Samples: Approach Boundaries



NFPA 70E® tables contain vital information about approach boundaries, hazard categories and PPE. **The following is only a SAMPLE of the information contained in NFPA 70E and should not be used for anything other than completing course activities.** Always use the most current edition of the NFPA 70E when working on energized electrical equipment. You can purchase the latest standards at the NFPA website.

Electrical Safety in the Workplace® and NFPA70E® are registered trademarks of the National Fire Protection Association, Quincy, MA.

Tables reproduced with permission from NFPA 70E®-2018, *Electrical Safety in the Workplace*, National Fire Protection Association. This reprinted material is not the complete and official position of the NFPA on the referenced subject, which is represented solely by the standard in its entirety.

Table 130.4(D)(a) Shock Protection Approach Boundaries to Exposed Energized Electrical Conductors or Circuit Parts for Alternating-Current Systems

(1) Nominal System Voltage Range, Phase to Phase ^a	(2) Limited Approach Boundary ^b		(4) Restricted Approach Boundary ^b ; Includes Inadvertent Movement Adder
	Exposed Movable Conductor ^c	Exposed Fixed Circuit Part	
Less than 50 V	Not specified	Not specified	Not specified
50 V–150 V ^d	3.0 m (10 ft 0 in.)	1.0 m (3 ft 6 in.)	Avoid contact
151 V–750 V	3.0 m (10 ft 0 in.)	1.0 m (3 ft 6 in.)	0.3 m (1 ft 0 in.)
751 V–15 kV	3.0 m (10 ft 0 in.)	1.5 m (5 ft 0 in.)	0.7 m (2 ft 2 in.)
15.1 kV–36 kV	3.0 m (10 ft 0 in.)	1.8 m (6 ft 0 in.)	0.8 m (2 ft 9 in.)
36.1 kV–46 kV	3.0 m (10 ft 0 in.)	2.5 m (8 ft 0 in.)	0.8 m (2 ft 9 in.)
46.1 kV–72.5 kV	3.0 m (10 ft 0 in.)	2.5 m (8 ft 0 in.)	1.0 m (3 ft 6 in.)
72.6 kV–121 kV	3.3 m (10 ft 8 in.)	2.5 m (8 ft 0 in.)	1.0 m (3 ft 6 in.)
138 kV–145 kV	3.4 m (11 ft 0 in.)	3.0 m (10 ft 0 in.)	1.2 m (3 ft 10 in.)
161 kV–169 kV	3.6 m (11 ft 8 in.)	3.6 m (11 ft 8 in.)	1.3 m (4 ft 3 in.)
230 kV–242 kV	4.0 m (13 ft 0 in.)	4.0 m (13 ft 0 in.)	1.7 m (5 ft 8 in.)
345 kV–362 kV	4.7 m (15 ft 4 in.)	4.7 m (15 ft 4 in.)	2.8 m (9 ft 2 in.)
500 kV–550 kV	5.8 m (19 ft 0 in.)	5.8 m (19 ft 0 in.)	3.6 m (11 ft 8 in.)
765 kV–800 kV	7.2 m (23 ft 9 in.)	7.2 m (23 ft 9 in.)	4.9 m (15 ft 11 in.)

Notes:

(1) For arc flash boundary, see 130.5(A).

(2) All dimensions are distance from exposed energized electrical conductors or circuit part to employee.

^aFor single-phase systems above 250 volts, select the range that is equal to the system's maximum phase-to-ground voltage multiplied by 1.732.

^bSee definition in Article 100 and text in 130.4(D)(2) and Informative Annex C for elaboration.

^c*Exposed movable conductors* describes a condition in which the distance between the conductor and a person is not under the control of the person. The term is normally applied to overhead line conductors supported by poles.

^dThis includes circuits where the exposure does not exceed 120 volts nominal.

Table 130.4(D)(b) Shock Protection Approach Boundaries to Exposed Energized Electrical Conductors or Circuit Parts for Direct-Current Voltage Systems

(1) Nominal Potential Difference	(2) Limited Approach Boundary		(4) Restricted Approach Boundary; Includes Inadvertent Movement Adder
	Exposed Movable Conductor ^a	Exposed Fixed Circuit Part	
Less than 50 V	Not specified	Not specified	Not specified
50 V–300 V	3.0 m (10 ft 0 in.)	1.0 m (3 ft 6 in.)	Avoid contact
301 V–1 kV	3.0 m (10 ft 0 in.)	1.0 m (3 ft 6 in.)	0.3 m (1 ft 0 in.)
1.1 kV–5 kV	3.0 m (10 ft 0 in.)	1.5 m (5 ft 0 in.)	0.5 m (1 ft 5 in.)
5 kV–15 kV	3.0 m (10 ft 0 in.)	1.5 m (5 ft 0 in.)	0.7 m (2 ft 2 in.)
15.1 kV–45 kV	3.0 m (10 ft 0 in.)	2.5 m (8 ft 0 in.)	0.8 m (2 ft 9 in.)
45.1 kV–75 kV	3.0 m (10 ft 0 in.)	2.5 m (8 ft 0 in.)	1.0 m (3 ft 6 in.)
75.1 kV–150 kV	3.3 m (10 ft 8 in.)	3.0 m (10 ft 0 in.)	1.2 m (3 ft 10 in.)
150.1 kV–250 kV	3.6 m (11 ft 8 in.)	3.6 m (11 ft 8 in.)	1.6 m (5 ft 3 in.)
250.1 kV–500 kV	6.0 m (20 ft 0 in.)	6.0 m (20 ft 0 in.)	3.5 m (11 ft 6 in.)
500.1 kV–800 kV	8.0 m (26 ft 0 in.)	8.0 m (26 ft 0 in.)	5.0 m (16 ft 5 in.)

Note: All dimensions are distance from exposed energized electrical conductors or circuit parts to worker.

^a*Exposed movable conductor* describes a condition in which the distance between the conductor and a person is not under the control of the person. The term is normally applied to overhead line conductors supported by poles.

NFPA 70E Table Samples: Likelihood of Occurrence

130.6

ARTICLE 130 — WORK INVOLVING ELECTRICAL HAZARDS

Table 130.5(C) Estimate of the Likelihood of Occurrence of an Arc Flash Incident for ac and dc Systems

Task	Equipment Condition	Likelihood of Occurrence*
Reading a panel meter while operating a meter switch.	Any	No
Performing infrared thermography and other non-contact inspections outside the restricted approach boundary. This activity does not include opening of doors or covers.		
Working on control circuits with exposed energized electrical conductors and circuit parts, nominal 125 volts ac or dc, or below without any other exposed energized equipment over nominal 125 volts ac or dc, including opening of hinged covers to gain access.		
Examination of insulated cable with no manipulation of cable.		
For dc systems, insertion or removal of individual cells or multi-cell units of a battery system in an open rack.		
For dc systems, maintenance on a single cell of a battery system or multi-cell units in an open rack.		
For ac systems, work on energized electrical conductors and circuit parts, including voltage testing.	Any	Yes
For dc systems, working on energized electrical conductors and circuit parts of series-connected battery cells, including voltage testing.		
Removal or installation of CBs or switches.		
Opening hinged door(s) or cover(s) or removal of bolted covers (to expose bare, energized electrical conductors and circuit parts). For dc systems, this includes bolted covers, such as battery terminal covers.		
Application of temporary protective grounding equipment, after voltage test.		
Working on control circuits with exposed energized electrical conductors and circuit parts, greater than 120 volts.		
Insertion or removal of individual starter buckets from motor control center (MCC).		
Insertion or removal (racking) of circuit breakers (CBs) or starters from cubicles, doors open or closed.		
Insertion or removal of plug-in devices into or from busways.		
Examination of insulated cable with manipulation of cable.		
Working on exposed energized electrical conductors and circuit parts of equipment directly supplied by a panelboard or motor control center.		
Insertion or removal of revenue meters (kW-hour, at primary voltage and current).		
Removal of battery conductive intercell connector covers.		
For dc systems, working on exposed energized electrical conductors and circuit parts of utilization equipment directly supplied by a dc source.		
Opening voltage transformer or control power transformer compartments.		
Operation of outdoor disconnect switch (hookstick operated) at 1 kV through 15 kV.		
Operation of outdoor disconnect switch (gang-operated, from grade) at 1 kV through 15 kV.		
Operation of a CB, switch, contactor, or starter.	Normal	No
Voltage testing on individual battery cells or individual multi-cell units.		
Removal or installation of covers for equipment such as wireways, junction boxes, and cable trays that does not expose bare, energized electrical conductors and circuit parts.		

NFPA 70E Table Samples: PPE Categories

130.7

ARTICLE 130 — WORK INVOLVING ELECTRICAL HAZARDS

Table 130.7(C)(15)(a) Arc-Flash PPE Categories for Alternating Current (ac) Systems

Equipment	Arc-Flash PPE Category	Arc-Flash Boundary
Panelboards or other equipment rated 240 volts and below Parameters: Maximum of 25 kA available fault current; maximum of 0.05 sec (2 cycles) fault clearing time; minimum working distance 455 mm (18 in.)	1	485 mm (19 in.)
Panelboards or other equipment rated greater than 240 volts and up to 600 volts Parameters: Maximum of 25 kA available fault current; maximum of 0.05 sec (2 cycles) fault clearing time; minimum working distance 455 mm (18 in.)	2	900 mm (3 ft)
600-volt class motor control centers (MCCs) Parameters: Maximum of 65 kA available fault current; maximum of 0.05 sec (2 cycles) fault clearing time; minimum working distance 455 mm (18 in.)	2	1.5 m (5 ft)
600-volt class motor control centers (MCCs) Parameters: Maximum of 42 kA available fault current; maximum of 0.33 sec (20 cycles) fault clearing time; minimum working distance 455 mm (18 in.)	4	4.3 m (14 ft)
600-volt class switchgear (with power circuit breakers or fused switches) and 600-volt class switchboards Parameters: Maximum of 35 kA available fault current; maximum of up to 0.5 sec (30 cycles) fault clearing time; minimum working distance 455 mm (18 in.)	4	6 m (20 ft)
Other 600-volt class (277 volts through 600 volts, nominal) equipment Parameters: Maximum of 65 kA available fault current; maximum of 0.05 sec (2 cycles) fault clearing time; minimum working distance 455 mm (18 in.)	2	1.5 m (5 ft)
NEMA E2 (fused contactor) motor starters, 2.3 kV through 7.2 kV Parameters: Maximum of 35 kA available fault current; maximum of up to 0.24 sec (15 cycles) fault clearing time; minimum working distance 910 mm (36 in.)	4	12 m (40 ft)
Metal-clad switchgear, 1 kV through 15 kV Parameters: Maximum of 35 kA available fault current; maximum of up to 0.24 sec (15 cycles) fault clearing time; minimum working distance 910 mm (36 in.)	4	12 m (40 ft)
Arc-resistant switchgear 1 kV through 15 kV [for clearing times of less than 0.5 sec (30 cycles) with an available fault current not to exceed the arc-resistant rating of the equipment], and metal-enclosed interrupter switchgear, fused or unfused of arc-resistant-type construction, 1 kV through 15 kV Parameters: Maximum of 35 kA available fault current; maximum of up to 0.24 sec (15 cycles) fault clearing time; minimum working distance 910 mm (36 in.)	N/A (doors closed) 4 (doors open)	N/A (doors closed) 12 m (40 ft)
Other equipment 1 kV through 15 kV Parameters: Maximum of 35 kA available fault current; maximum of up to 0.24 sec (15 cycles) fault clearing time; minimum working distance 910 mm (36 in.)	4	12 m (40 ft)

Note: For equipment rated 600 volts and below and protected by upstream current-limiting fuses or current-limiting circuit breakers sized at 200 amperes or less, the arc flash PPE category can be reduced by one number but not below arc flash PPE category 1.

Informational Note to Table 130.7(C)(15)(a): The following are typical fault clearing times of overcurrent protective devices:

- (1) 0.5 cycle fault clearing time is typical for current limiting fuses when the fault current is within the current limiting range.
- (2) 1.5 cycle fault clearing time is typical for molded case circuit breakers rated less than 1000 volts with an instantaneous integral trip.
- (3) 3.0 cycle fault clearing time is typical for insulated case circuit breakers rated less than 1000 volts with an instantaneous integral trip or relay operated trip.
- (4) 5.0 cycle fault clearing time is typical for relay operated circuit breakers rated 1 kV to 35 kV when the relay operates in the instantaneous range (i.e., "no intentional delay").
- (5) 20 cycle fault clearing time is typical for low-voltage power and insulated case circuit breakers with a short time fault clearing delay for motor inrush.
- (6) 30 cycle fault clearing time is typical for low-voltage power and insulated case circuit breakers with a short time fault clearing delay without instantaneous trip.

Informational Note No. 1: See Table 1 of IEEE 1584TM, *Guide for Performing Arc Flash Hazard Calculations*, for further information regarding Notes b through d.

Informational Note No. 2: An example of a standard that provides information for arc-resistant switchgear referred to in Table 130.7(C)(15)(a) is IEEE C37.20.7, *Guide for Testing Metal-Enclosed Switchgear Rated Up to 38 kV for Internal Arcing Faults*.

Table 130.7(C) (15)(b) Arc-Flash PPE Categories for Direct Current (dc) Systems

Equipment	Arc-Flash PPE Category	Arc-Flash Boundary
Storage batteries, dc switchboards, and other dc supply sources Parameters: Greater than or equal to 100 V and less than or equal to 250 V Maximum arc duration and minimum working distance: 2 sec @ 455 mm (18 in.)		
Available fault current less than 4 kA	2	900 mm (3 ft)
Available fault current greater than or equal to 4 kA and less than 7 kA	2	1.2 m (4 ft)
Available fault current greater than or equal to 7 kA and less than 15 kA	3	1.8 m (6 ft)
Storage batteries, dc switchboards, and other dc supply sources Parameters: Greater than 250 V and less than or equal to 600 V Maximum arc duration and minimum working distance: 2 sec @ 455 mm (18 in.)		
Available fault current less than 1.5 kA	2	900 mm (3 ft)
Available fault current greater than or equal to 1.5 kA and less than 3 kA	2	1.2 m (4 ft)
Available fault current greater than or equal to 3 kA and less than 7 kA	3	1.8 m (6 ft)
Available fault current greater than or equal to 7 kA and less than 10 kA	4	2.5 m (8 ft)

Notes

(1) Apparel that can be expected to be exposed to electrolyte must meet both of the following conditions:

- (a) Be evaluated for electrolyte protection

Informational Note: ASTM F1296, *Standard Guide for Evaluating Chemical Protective Clothing*, contains information on evaluating apparel for protection from electrolyte.

- (b) Be arc-rated

Informational Note: ASTM F1891, *Standard Specifications for Arc Rated and Flame Resistant Rainwear*, contains information on evaluating arc-rated apparel.

(2) A two-second arc duration is assumed if there is no overcurrent protective device (OCPD) or if the fault clearing time is not known. If the fault clearing time is known and is less than 2 seconds, an incident energy analysis could provide a more representative result.

Informational Note No. 1: When determining available fault current, the effects of cables and any other impedances in the circuit should be included. Power system modeling is the best method to determine the available short-circuit current at the point of the arc. Battery cell short-circuit current can be obtained from the battery manufacturer. See Informative Annex D.5 for the basis for table values and alternative methods to determine dc incident energy. Methods should be used with good engineering judgment.

Informational Note No. 2: The methods for estimating the dc arc-flash incident energy that were used to determine the categories for this table are based on open-air incident energy calculations. Open-air calculations were used because many battery systems and other dc process systems are in open areas or rooms. If the specific task is within an enclosure, it would be prudent to consider additional PPE protection beyond the value shown in this table. Research with ac arc flash has shown a multiplier of as much as 3× for arc-in-a-box [508 mm (20 in.) cube] versus open air. Engineering judgment is necessary when reviewing the specific conditions of the equipment and task to be performed, including the dimensions of the enclosure and the working distance involved.

NFPA 70E Table Sample: PPE

130.7

ARTICLE 130 — WORK INVOLVING ELECTRICAL HAZARDS

Table 130.7(C)(15)(c) Personal Protective Equipment (PPE)

Arc-Flash PPE Category	PPE
1	<p>Arc-Rated Clothing, Minimum Arc Rating of 4 cal/cm² (16.75 J/cm²)^a Arc-rated long-sleeve shirt and pants or arc-rated coverall Arc-rated face shield^b or arc flash suit hood Arc-rated jacket, parka, rainwear, or hard hat liner (AN) Protective Equipment Hard hat Safety glasses or safety goggles (SR) Hearing protection (ear canal inserts)^c Heavy-duty leather gloves^d Leather footwear (AN)</p>
2	<p>Arc-Rated Clothing, Minimum Arc Rating of 8 cal/cm² (33.5 J/cm²)^a Arc-rated long-sleeve shirt and pants or arc-rated coverall Arc-rated flash suit hood or arc-rated face shield^b and arc-rated balaclava Arc-rated jacket, parka, rainwear, or hard hat liner (AN) Protective Equipment Hard hat Safety glasses or safety goggles (SR) Hearing protection (ear canal inserts)^c Heavy-duty leather gloves^d Leather footwear</p>
3	<p>Arc-Rated Clothing Selected so That the System Arc Rating Meets the Required Minimum Arc Rating of 25 cal/cm² (104.7 J/cm²)^a Arc-rated long-sleeve shirt (AR) Arc-rated pants (AR) Arc-rated coverall (AR) Arc-rated arc flash suit jacket (AR) Arc-rated arc flash suit pants (AR) Arc-rated arc flash suit hood Arc-rated gloves^d Arc-rated jacket, parka, rainwear, or hard hat liner (AN) Protective Equipment Hard hat Safety glasses or safety goggles (SR) Hearing protection (ear canal inserts)^c Leather footwear</p>
4	<p>Arc-Rated Clothing Selected so That the System Arc Rating Meets the Required Minimum Arc Rating of 40 cal/cm² (167.5 J/cm²)^a Arc-rated long-sleeve shirt (AR) Arc-rated pants (AR) Arc-rated coverall (AR) Arc-rated arc flash suit jacket (AR) Arc-rated arc flash suit pants (AR) Arc-rated arc flash suit hood Arc-rated gloves^d Arc-rated jacket, parka, rainwear, or hard hat liner (AN) Protective Equipment Hard hat Safety glasses or safety goggles (SR) Hearing protection (ear canal inserts)^c Leather footwear</p>

AN: As needed (optional). AR: As required. SR: Selection required.

^aArc rating is defined in Article 100.

^bFace shields are to have wrap-around guarding to protect not only the face but also the forehead, ears, and neck, or, alternatively, an arc-rated arc flash suit hood is required to be worn.

^cOther types of hearing protection are permitted to be used in lieu of or in addition to ear canal inserts provided they are worn under an arc-rated arc flash suit hood.

^dIf rubber insulating gloves with leather protectors are used, additional leather or arc-rated gloves are not required. The combination of rubber insulating gloves with leather protectors satisfies the arc flash protection requirement.